

## INVISION Wireless Dream Controller

Šifra: 6413

Kategorija proizvoda: Napajanja i kontroleri za Led

Proizvođač: INVISION

**Cena: 3.980,00 rsd**

Working temperature: -20- 60

consume power:2.2W

Length setup function

Memory function

INVISION Wireless Dream Controller

**Wireless Dream Controller**

*LED Controller*

This controller is design for led production which uses ZJ168 as driver, it is very useful for light box advertisement, stage light, house decorating, and so on

Supply voltage: DC12V

Output: Tow group SPI signal

A lot of programs to chose

With digital tube, left two reveal the mode, right two reveal the speed

### Product Description

General description

This controller is design for LED production which use HL1606 as driver, it is very useful

For light box advertisement, stage light, house decorating, and so on.

Specification

Working temperature: -20- 60 ° C Supply voltage: DC12V

Product size: L90× W60× H25mm Weight: 75g

Consume power: 2.2W Output: Tow group SPI signal

Function&Feature

Length setup funtion A lot of programs to chose

Memory function 128\*128\*128 grayscale

Function of controller pannel

ON/OFF button, it can open or close LED anytime, when LED is on the station of closing, The LCD will display "IC NUMBER: \*\*\*", "\*\*\*\*" is the value of current setting.

Play/pause button, when you want to see the static effection of LED, you may press this button to pause.

Adding button, to add the IC NUMBER, the most number is 255 (510 group of RGB)

Reducing button, to reduce the IC NUMBER, the least number is 16 (32 group of RGB)

Program chosing button, up direction, there are 83 programs in all.

Program chosing button, down direction.

Speed slow button, there are 100 step in all, the most number is 100

Speed quick button, the least number is 1

Function of remote pannel

ON/OFF: ON/OFF button, it can open or close LED anytime, when LED is on the station of closing, The LCD will display "IC NUMBER: \*\*\*", "\*\*\*\*" is the value of current setting.

MODE: Play/pause button, when you want to see the static effection of LED, you may press this button to pause.

S+: Speed quick button, the least number is 1

S-: Speed slow button, there are 100 step in all, the most number is 100

B+: Program chosing button, up direction, there are 83 programs in all.

B-: Program chosing button, down direction.

OUTPUT1&OUTPUT2 Description: L, K, D, S is the corresponding signal of HL1606, which is L\_I, CK\_I, D\_I, S\_I.

PROGRAM Description: (Condition: A1\_chBlue LED; A2\_Red LED; A3\_Green LED)

| PROGRAM | Function                                    | PROGRAM | Function   |
|---------|---|---------|--|
| 1       | All color wave forward direction            | 43      | Change color red-purple-red lower curtain        |
| 2       | All color wave backward direction           | 44      | Change color red-yellow-red forward direction    |
| 3       | All color draw curtain by waving            | 45      | Change color red-yellow-red backward direction   |
| 4       | All color lower curtain by waving           | 46      | Change color red-yellow-red draw curtain         |
| 5       | Three color wave by wave forward direction  | 47      | Change color red-yellow-red lower curtain        |
| 6       | Three color wave by wave backward direction | 48      | Change color red-green-red forward direction     |
| 7       | Three color draw curtain waving by waving   | 49      | Change color red-green-red backward direction    |
| 8       | Three color lower curtain waving by waving  | 50      | Change color red-green-red draw curtain          |
| 9       | Many color wave forward direction           | 51      | Change color red-green-red lower curtain         |
| 10      | Many color wave backward direction          | 52      | Change color red-blue-red forward direction      |
| 11      | Many color wave draw curtain                | 53      | Change color red-blue-red backward direction     |
| 12      | Many color wave lower curtain               | 54      | Change color red-blue-red draw curtain           |
| 13      | Six color trail forward direction           | 55      | Change color red-blue-red lower curtain          |
| 14      | Six color trail backward direction          | 56      | Change color green-cyan-green forward direction  |
| 15      | Six color trail draw curtain                | 57      | Change color green-cyan-green backward direction |
| 16      | Six color trail lower curtain               | 58      | Change color green-cyan-green draw curtain       |
| 17      | Three base color trail forward direction    | 59      | Change color green-cyan-green lower curtain      |
| 18      | Three base color trail backward direction   | 60      | Change color green-blue-green forward direction  |
| 19      | Three base color trail draw curtain         | 61      | Change color green-blue-green backward direction |
| 20      | Three base color trail lower curtain        | 62      | Change color green-blue-green draw curtain       |
| 21      | Six color jumpy change                      | 63      | Change color green-blue-green lower curtain      |
| 22      | Three base color jumpy change               | 64      | Change color red-white-red forward direction     |
| 23      | Three mixxing color jumpy change            | 65      | Change color red-white-red backward direction    |
| 24      | Six color jumpy change forward direction    | 66      | Change color red-white-red draw curtain          |

|    |  |    |  |
|----|--|----|--|
| 25 | Six color jumpy change backward direction        | 67 | Change color red-white-red lower direction               |
| 26 | Six color jumpy change draw curtain              | 68 | Change color green-white-green forward direction         |
| 27 | Six color jumpy change lower curtain             | 69 | Change color green-white-green backward direction        |
| 28 | Three base color jumpy change forward direction  | 70 | Change color green-white-green draw curtain              |
| 29 | Three base color jumpy change backward direction | 71 | Change color green-white-green lower direction           |
| 30 | Three base color jumpy change draw curtain       | 72 | Change color blue-white-blue forward direction           |
| 31 | Three base color jumpy change lower curtain      | 73 | Change color blue-white-blue backward direction          |
| 32 | Six color brush forward direction                | 74 | Change color blue-white-blue draw curtain                |
| 33 | Six color brush backward direction               | 75 | Change color blue-white-blue lower curtain               |
| 34 | Three base color brush forward direction         | 76 | Six color fade in and fade out forward direction         |
| 35 | Three base color brush backward direction        | 77 | Six color fade in and fade out backward direction        |
| 36 | Six color brush draw curtain                     | 78 | Six color fade in and fade out draw curtain              |
| 37 | Six color brush lower curtain                    | 79 | Six color fade in and fade out lower curtain             |
| 38 | Three base color brush draw curtain              | 80 | Three base color fade in and fade out forward direction  |
| 39 | Three base color brush lower curtain             | 81 | Three base color fade in and fade out backward direction |
| 40 | Change color red-purple-red forward direction    | 82 | Three base color fade in and fade out draw curtain       |
| 41 | Change color red-purple-red backward direction   | 83 | Three base color fade in and fade out lower curtain      |
| 42 | Change color red-purple-red draw curtain         | 84 | Autoplay 1~83  |