

## ARCAM A29 Integrirano Pojačalo

# ARCAM A29 Integrirano Pojačalo

Šifra: 10548

Kategorija proizvoda: Integrirana Pojačala

Proizvođač: ARCAM

Cena: **95.880,00** rsd

With a class G amplifier, toroidal based power supply, acoustically damped chassis, complementary transistor output stages and exceptionally low levels of distortion and noise the A29 is capable of reproducing music with all its original authority and detail. Rest assured you will be hearing the music just as the artist intended.

The A29 have been designed to leapfrog the competition with a massive 80 watts per channel into 8 ohms and 175 watts into 4 ohms, allowing for huge extra power reserves from our latest generation class G topology that is both clever and efficient. During normal operation, distortion is measured in less than one part per million so that this massive power is deliver with total control and finesse.

There have been great strides made in improving audio sources and loudspeakers in recent years and the time is right to match them in the field of amplifier design. This ground breaking amplifier is a must audition amplifiers for music lovers who understand that power is nothing without control.

### Spec:

Continuous power output (20Hz—20kHz at 0.5% THD), per channel

Both channels, 8Ω, 20Hz—20kHz	80W
-------------------------------	-----

Single channel, 4Ω, at 1kHz	175W
-----------------------------	------

Harmonic distortion, 80% power, 8Ω at 1kHz	0.003%
--	--------

### Inputs

#### Phono (MM) cartridge:

Input sensitivity at 1kHz	5mV
---------------------------	-----

Input impedance	47kΩ + 100pF
-----------------	--------------

Frequency response (ref. RIAA curve)	20Hz - 20kHz ± 1dB
--------------------------------------	--------------------

Signal/Noise ratio (Awtd) 50W, ref. 5mV input	80dB
---	------

Overload margin, ref. 5mV at 1kHz	23dB
-----------------------------------	------

#### Inputs:

Nominal sensitivity	1V
---------------------	----

Input impedance	10kΩ
-----------------	------

Maximum input	4.6Vrms
---------------	---------

Frequency response	20Hz - 20kHz ± 0.2dB
--------------------	----------------------

Signal/noise ratio (Awtd) 50W, ref. 1V input	105dB
--	-------

#### Preamplifier output

Nominal output level	735mV
----------------------	-------

Output impedance	230Ω
------------------	------

#### Headphone output

Maximum output level into 600Ω	5V
--------------------------------	----

Output impedance	1Ω
------------------	----

Load range	16Ω - 2kΩ
------------	-----------

#### Accessory power output

2.1mm DC connector	6V, 500mA
--------------------	-----------

General	
Mains voltage	110-120V or 220-240V
Power consumption (maximum)	500W
Dimensions W x D x H (including feet)	433 x 275 x 85mm
Weight (net)	9.2kg
Weight (packed)	10.7kg
<b>Supplied accessories</b>	Mains lead
	CR902 remote control
	2 x AAA batteries
	Accessory power cable