

## ARX MixxMaker Line Mic Mixer - Višezonska mikseta

Šifra: 14818  
Kategorija proizvoda: Višezonske Miksete  
Proizvođač: ARX

**Cena: 88.452,00 rsd**

### Great Features

The Wireless audio receiver, USB connector and the Minijack inputs all have their own individual level controls.

Each Microphone channel on the MIXXMaker has a Balanced Low Noise Mic input, plus individual Gain and Level controls. The Mic input can also be switched to be a Line input as required. Switchable Phantom power is also available on both Mic Inputs.

The Stereo Line Inputs 3/4 and 5/6 each have rear panel input trim controls, as well as front panel output level controls, and their inputs are industry standard RCA type connectors.

Additionally there are Left and Right Master controls, and a mono L+R Aux Output with its own level control. The Left and Right Master Output XLR connectors can also be switched to Mono if required, by a rear panel switch.

The rear panel also has a connector for a push-to-talk jack, and a Priority override ducker switch for Channel 1. Pressing this switch in will duck the level of the other channels by 20dB when Channel 1 is used.

### LED Indicators

The front panel has LED indicators for Wireless audio (see Specifications below), USB active, Priority Override enabled, Phantom Power enabled, Outputs switched to Mono, and AC power.

### AC Power

It is available as a **100 to 120V AC** model or a **220 to 240V AC** model, and AC power is connected to the unit via a standard three pin IEC connector, with built-in fuse and voltage change switch.

The **ARX MIXXMaker** is an intuitive, user-friendly Master mixer, capable of handling all commonly used current audio interfaces. In other words, a total solution to today's install requirements.

Has **Wireless audio, USB and Minijack** inputs!

**Plus** 2 x Balanced XLR Mic / Line Inputs

**Plus** 2 x stereo Line In channels

Global 3 way EQ control

Switchable Phantom power

Switchable push-to-talk with a Priority override ducker for Mic channel 1

User-friendly layout in 1 RU package

Flawless performance in any audio environment

ARX MixxMaker Line Mic Mixer - Višezonska mikseta

with all these audio sources. ARX introduces the **MIXXMaker** - a new multi-channel Mic/Line Master Mixer. This unique device features **Wireless audio, USB and Minijack** inputs, **2 Mic/Line** inputs, **2 stereo line** inputs, and **Left/Right (or Zone 1 and 2) Master** level controls, as well as an Auxiliary mono output with its own level control.

That's a lot of Inputs and a lot of control in a compact, user-friendly unit only **1 RU** tall!

## MIXXMaker Specifications

**Microphone Inputs:** Electronically Balanced on XLR Connectors

**Stereo Line Inputs:** Line level inputs on RCA Connectors

**Mic Priority** Switchable Channel 1 override; 20dB attenuation to all other channels

**Input Gain:** Variable 0dB to 60dB on Mic/Line channels by rear panel trim control, plus Mic/Line input switch (-20dB)

**Channel Level:** Infinity to +6dB Gain

---

### Mic and Line Channel EQ:

Low 100Hz 15dB Cut/Boost Shelving

Mid 800HZ 15dB Cut/Boost Bell, Broad Q

High 10KHz 15dB Cut/Boost Shelving

**Frequency Response:** 20-20KHz +or- 1dB

**Distortion:** Below .005% 100Hz to 10KHz

**Phantom Power:** +48VDC switchable on all Microphone Inputs

---

## Wireless audio Receiver Specifications

<b>Range:</b>	Approx 2 - 4 metres	Depends on paired source device
<b>LED Indicators:</b>	<b>Scan Red LED</b>	<b>Red LED Flashes</b>
	<b>Lock Blue LED</b>	<b>Matching/Pairing: Blue LED Flashes</b>
		<b>Matched/Paired: Blue LED On</b>
<b>Frequency</b>	<b>2.402 - 2.480 GHz</b>	
<b>Sensitivity</b>	<b>-90dBm @0.1% BER</b>	

---

**Master Outputs:** Electronically Balanced XLR 300 ohms Line Level

**Master Outputs Signal/Noise:** -90dB unweighted.

**Max Output Level:** +20dB

---

## **USB Specifications**

**Input Connector** USB type B port

**Codec** 24 bit High Resolution

**USB Power** Operating current via USB Port 80mA

**MIXXMaker AC Power:** Supplied as 100-120 VAC model or 220-240 VAC model 50/60HZ 8VA (8 watts) 3 pin IEC connector with removable cable