

## FOCUSRITE REDNET X2P - Zvučna kartica

Šifra: 15642

Kategorija proizvoda: Ethernet i PCIe Zvučne kartice

Proizvođač: Focusrite

Cena: **107.880,00** rsd

A local input mixer allows monitoring control for people who want to hear their parts louder over the mix. Conversely, a control lockout parameter ensures your settings remain unchanged when used remotely.

On the rear of the interface you'll find two locking, combination XLR-1/4" inputs, as well as two level-controlled XLR outputs that can go up to 24 dBu. On the front of interface, your 1/4" headphone output is powered by an amplifier capable of driving both low- and high-impedance headphones. The Red Evolution mic pres provide clean gain, phantom power, high-pass filtering at 80 Hz, per-channel polarity reversing, and an Air mode that emulates the sound of Focusrite's classic transformer-based mic preamps, giving you a boost at 10 and 20 kHz respectively.

The X2P can capture and reproduce audio at sample rates and resolutions of up to 96 kHz and 24 bits. On the output side, the RedNet X2P provides a dynamic range of 120 dB at line level and 117 dB for the headphones. Built out of aluminum and steel, the unit is quite sturdy and can be mounted directly to a mic stand, which keeps it out of the way yet within reach.

### Key Features at a Glance

- Stereo 2x2 audio interface for Dante AoIP networks
- Two Red Evolution mic preamps for mic, line, or instrument level inputs
- Power-over-Ethernet supplied: IEEE 802.3af compliant
- Up to 24-bit, 96 kHz sampling rates
- Robust steel and aluminum chassis
- Local input mix to allow personalized monitoring
- Powerful headphone output, even with high-impedance headphones
- Local control lockout of mic settings, output settings, or both
- Up to 24 dBu line output levels
- Independent level control of headphone and line outputs
- Mute switch for line output
- Mic stand mount
- Kensington security slot
- Integrated network switch allows daisy-chaining of network devices
- Includes Brainworx bx\_console Focusrite, a plug-in that faithfully captures the sound, feel, and style of the original Focusrite ISA 110 Equalizer and ISA 130 Dynamics Modules

### Focusrite X2P 2x2 Specs

- Form Factor Desktop
- Display 1 x LCD
- Channels of I/O 2 Input / 2 Output
- Number of Microphone Preamps 2 Preamps
- Signal Processing
- Gain/Trim Range Hi-Z Inputs: 0 to 68 dB

Mic Inputs:  
0 to 68 dB  
Connectivity  
Analog Audio I/O 2 x Combo XLR-1/4" TRS Mic/Line Input  
1 x 1/4" TRS Headphone Output  
2 x XLR 3-Pin Monitor Output  
Phantom Power 48 V (Selectable on Individual Inputs)  
Digital Audio I/O None  
Host Connection / USB None  
Host Connection Protocol None  
USB (Non-Host) None  
Sync I/O None  
Network I/O 1 x etherCON/RJ45 Dante  
1 x etherCON/RJ45 Dante (PoE)  
MIDI I/O None  
Performance  
Frequency Response Hi-Z Inputs:  
20 Hz to 35 kHz  $\pm 0.1$  dB  
Mic, Line Inputs:  
20 Hz to 35 kHz  $\pm 0.1$  dB  
Maximum Input Level Hi-Z Inputs:  
+15 dBu (Min Gain)  
Mic Inputs:  
+24 dBu (Min Gain)  
Impedance Hi-Z Inputs:  
2 Megohms  
Mic/Line Inputs:  
6.2 Kilohms  
Dynamic Range Mic/Line Inputs:  
120 dBA  
SNR Hi-Z Inputs:  
118 dBA  
Mic/Line Inputs:  
120 dBA  
THD+N Hi-Z Inputs:  
< -100 dB / < 0.001%  
Inputs:  
< -103 dB / < 0.0007%  
Crosstalk Headphone Outputs:  
< -85 dB  
Inputs:  
< -72 dB  
System:  
< -159 dB  
EIN Mic/Line Inputs:  
< -130 dBu A-Weighted  
CMRR Mic/Line Inputs:  
-80 dB  
Line Outputs:  
-80 dB  
Digital Audio  
Sample Rates 44.1 / 48 / 88.2 / 96 kHz  
Bit Depths 24-Bit (AD/DA Conversion)  
Power  
Power Requirements AC/DC Power Adapter (Included)  
AC/DC Power Adapter 12 VDC at 1.2 A (Included)  
Power Consumption 13.3 W  
Physical  
Operating Temperature 113°F / 45°C  
Dimensions 5.5 x 4.1 x 1.9" / 140 x 104 x 47.5 mm  
Weight 2.3 lb / 1.0 kg

#### Packaging Info

Package Weight 4.25 lb

Box Dimensions (LxWxH) 15 x 7.9 x 4.85"