

MARANTZ CD5005 Black

## MARANTZ CD5005 Black

Šifra: 9893  
 Kategorija proizvoda: CD Plejeri  
 Proizvođač: Marantz

Cena: **35.880,00** rsd

ONKYO R-N855 B

The new CD5005 incorporates everything its predecessor, the CD5004, offered including the Marantz-own HDAM-SA2, but this year it features an upgraded DAC CS4398 and new CD mechanism - both taken from its big brother, the CD6005. As you'd expect, it plays CD, CD-R and CD-RW discs as well as MP3 and WMA files. It includes customised components for sound tuning and an extra-reliable CD transport mechanism. The Audio EX(clusive) mode further enhances sound quality by switching off functions such as digital output and pitch control when not in use. The random play function will give you another option to explore your music in a new way. Also new for this year is an upgraded remote controller as well as low-power stand-by and auto stand-by modes. In addition, high-grade gold-plated analogue outputs guarantee best connectivity, while a well-defined headphone output, and an easy to read display rounds off this excellent player.

### Features

Disc Capacity	1
CD Compatibility: CD / CD-R/RW / SA-CD / WMA / MP3 / AAC	o / o / - / o / o / -
CD-Text / SA-CD Text / ID3 Tag / WMA Meta Tag / AAC Meta data	o / - / o / o / -
HDAM version	SA2
Power Transformer: Toroidal / EI	- / o
High Grade Audio Components	o
Symmetric circuit layout	o
Digital out off / Audio EX Mode	o / o
Headphone: Standard / Buffer / Current feedback	- / o (HDAM-SA2) / -

### Others

Separated rectifier circuit for analogue and digital circuitry	o
System block shielding: copper / metal / none	- / - / o
Display: Dimmer / Off	o / o

## Playback

Program Play (CD) Repeat	25 o
Random Play Pitch Control	o o

## Inputs/Outputs

Analogue Out (Cinch) Digital Optical In / Out	2ch - / 1
Digital Coaxial In / Out Gold Plated Cinch	- / 1 o
D-Bus Headphone Out	o o
Headphone Volume Control	o

## Specifications

Mechanism D/A Conversion	CJDKT690 Multi-bit, Delta-Sigma
DAC IC Digital Filter	CS4398 CS4398
Noise Shaper Low Pass Filter stage	CS4398 NJM2068
Output Buffer Frequency Response	HDAM SA2 20 Hz - 20 kHz
Dynamic Range Signal to Noise Ratio	100 dB 110 dB
Total Harmonic Distortion Channel Separation	0.002% 98 dB

## General

Available colors: Gold / Silver / Black / Silver-Gold Metal Front Panel	- / - / o / o o
Remote Control Power Consumption in W	RC002PMCD 14
Standby Consumption in W Auto power off	0.3 o
Detachable Power Cable Maximum Dimensions (W x H x D) in mm	o 440 x 105 x 338
Weight in kg	5.0

