

## MARANTZ CD5005 Black

Šifra: 9893  
Kategorija proizvoda: CD Plejeri  
Proizvođač: Marantz

Cena: **35.880,00** rsd

ONKYO R-N855 B logo not found or type unknown

The new CD5005 incorporates everything its predecessor, the CD5004, offered including the Marantz-own HDAM-SA2, but this year it features an upgraded DAC CS4398 and new CD mechanism – both taken from its big brother, the CD6005. As you'd expect, it plays CD, CD-R and CD-RW discs as well as MP3 and WMA files. It includes customised components for sound tuning and an extra-reliable CD transport mechanism. The Audio EX(clusive) mode further enhances sound quality by switching off functions such as digital output and pitch control when not in use. The random play function will give you another option to explore your music in a new way. Also new for this year is an upgraded remote controller as well as low-power stand-by and auto stand-by modes. In addition, high-grade gold-plated analogue outputs guarantee best connectivity, while a well-defined headphone output, and an easy to read display rounds off this excellent player.

### Features

Disc Capacity	1
CD Compatibility: CD / CD-R/RW / SA-CD / WMA / MP3 / AAC	o / o / - / o / o / -
CD-Text / SA-CD Text / ID3 Tag / WMA Meta Tag / AAC Meta data	o / - / o / o / -
HDAM version	SA2
Power Transformer: Toroidal / EI	- / o
High Grade Audio Components	o
Symmetric circuit layout	o
Digital out off / Audio EX Mode	o / o
Headphone: Standard / Buffer / Current feedback	- / o (HDAM-SA2) / -

### Others

Separated rectifier circuit for analogue and digital circuitry	o
System block shielding: copper / metal / none	- / - / o
Display: Dimmer / Off	o / o

### Playback

Program Play (CD)	25
-------------------	----

Repeat	0
Random Play	0
Pitch Control	0
<b>Inputs/Outputs</b>	
Analogue Out (Cinch)	2ch
Digital Optical In / Out	- / 1
Digital Coaxial In / Out	- / 1
Gold Plated Cinch	0
D-Bus	0
Headphone Out	0
Headphone Volume Control	0
<b>Specifications</b>	
Mechanism	CJDKT690
D/A Conversion	Multi-bit, Delta-Sigma
DAC IC	CS4398
Digital Filter	CS4398
Noise Shaper	CS4398
Low Pass Filter stage	NJM2068
Output Buffer	HDAM SA2
Frequency Response	20 Hz - 20 kHz
Dynamic Range	100 dB
Signal to Noise Ratio	110 dB
Total Harmonic Distortion	0.002%
Channel Separation	98 dB
<b>General</b>	
Available colors: Gold / Silver / Black / Silver-Gold	- / - / 0 / 0
Metal Front Panel	0
Remote Control	RC002PMCD
Power Consumption in W	14
Standby Consumption in W	0.3
Auto power off	0
Detachable Power Cable	0
Maximum Dimensions (W x H x D) in mm	440 x 105 x 338
Weight in kg	5.0