

MACKIE Thump215 - Aktivni zvučnik

Šifra: 16858

Kategorija proizvoda: Aktivne Zvučne Kutije

Proizvođač: MACKIE

Cena: 53.880,00 rsd



Mikser **Thump215** ima dva XLR 1/4"-na Mic/Line kanala sa pripadajućim Gain kontrolama, dok XLR izlaz omogućava lako povezivanje dodatnih zvučnika u lanac. 3.5-milimetarski TRS Aux ulaz raspoloživ je na drugom kanalu, za povezivanje vašeg omiljenog prenosivog plejera. Čvrsta šasija otporna na bilo kakve spoljašnje uticaje garantuje da će uređaj biti sačuvan od potencijalnih oštećenja pri transportu. Na donjem delu kabineta prisutni su i žljebovi za montiranje. Tu je i mogućnost upotrebe **215XT**-a kao podnog monitora (ugaoni dizajn), za koncertni/izvođački monitoring na bini.

At a Glance

1400W ultraefficient Class-D amplifier

Built-Like-A-Tank to conquer every gig while lightweight for easy loading

Frequency response: 40 Hz to 20 kHz

Max SPL: 129 dB

15" high-performance woofer

1" compression driver

Built-in Feedback Eliminator reduces squeals and out of control rumble

Music Ducking mode automatically reduces the level of Ch.2 when Ch.1 receives signal

Standard pole mount

Monitor wedge provides optimal angle for use as a floor monitor

Universal power supply

Flexible Inputs / Outputs

Channel 1 features a combo XLR-1/4" input that accepts mic or line signals

Channel 2 features a combo XLR-1/4" line input plus stereo 3.5mm input

Thru output contains audio from both input channels

Performance for a New Generation

These are the loudest, most powerful, and best sounding Thump loudspeakers ever, and they are ready to take on your most demanding gigs. Completely redesigned from the ground up, Thump has beefier drivers, 1400W Class-D amplifiers, and powerful tools to make your next gig easier than ever.

Music Ducking

You've got music playing nice and loud, but it's time for another announcement. Sure, you could mess with your levels every time, but who's got time for that. Simply press the Music Ducking button, and channel 2 will automatically turn down whenever you speak into the mic on channel 1.

Feedback Eliminator

Ever get a little too up close and personal with the microphone only to hear a loud, ear-destroying squeal? That's commonly known as feedback. And it's an unfortunate issue that physics won't change its mind on. But wait! Hit the Feedback Eliminator button and laugh in the face of those silly acoustic laws.

Mackie Thump215 Specs

Configuration: Active 2-Way

Enclosure Type: Bass-Reflex Loudspeaker

Total Power Capacity: 1400 W Peak

Amplifier Class: Class-D

Drivers

HF Driver: 1 x 1" / 25.4 mm Titanium Dome Compression Driver

MF Driver: None

LF Driver: 1 x 15" / 381 mm Woofer

Performance

Frequency Response: 40 Hz to 20 kHz -10 dB

Maximum SPL: 129 dB SPL

Connectivity

Audio I/O: 2 x Combo XLR-1/4" TRS Balanced/Unbalanced Mic/Line Input

1 x 1/8" / 3.5 mm TRS Female Unbalanced Line Input

1 x XLR 3-Pin Male Balanced Line Output

Network I/O: None

USB: None

Wireless: Connectivity None

Signal Processing

EQ: None

Parametric EQ: None

Semi-Parametric EQ: None

Filters: None

Alignment Delay: None

Phase Adjustment: None

Power

AC Input Power - Universal:

100 to 240 VAC, 50 / 60 Hz

AC Power Connector: 1 x IEC

Power Consumption: 75 W

Physical

Mounting: 1 x Pole Socket (Bottom)

Handles: 1 x Each Side

1 x Top

Dimensions: 685.8 x 442 x 355.6 mm

Weight: 15.8 kg