

FOCUSRITE ISA One - Mikrofonsko pretpojačalo

Šifra: 16888
Kategorija proizvoda: Studijska Pretpojačala
Proizvođač: Focusrite

Cena: 71.400,00 rsd

FOCUSRITE ISA One - Mikrofonsko pretpojačalo

In addition to switchable input impedance settings for the microphone preamp, the unit includes a line input on XLR and 1/4" TRS phone jacks. An independent DI channel features a dedicated gain control, active or passive impedance switch, a 1/4" TRS output for routing to an amplifier, and an independent XLR output on the rear.

The ISA One features an insert point should the need arise to place extra signal processing between the preamp or DI, and the optional analog-to-digital

converter. Phantom power, phase reverse and a 75 Hz, 18 dB/octave high-pass filter are also available from the angled front fascia.

Independent input metering for both channels is provided by a moving coil VU meter with variable calibration to suit analog and digital recording media, alongside two six-LED peak meters. Inputs can be metered either pre or post insert. The meter calibrations utilize the same reference points as Avid's Pro Tools HD systems, allowing effortless integration with Pro Tools.

A premium bonus is the Brainworx bx_console Focusrite SC channel-strip plug-in, a stellar digital emulation of the legendary and rare Focusrite Studio Console. Only 10 of the consoles were ever produced, but you can access its famed sound directly in your DAW.

Classic single-channel Focusrite microphone preamp with Independent DI
Ideal for both engineers and demanding performers alike, featuring independent gain control, an output for routing to an amp, an independent XLR output on the rear and routing to the optional ADC

Four, carefully selected, switchable input-impedance levels (including the original ISA 110 setting), to match or enhance the performance of any microphone

Headphone output with volume control can feed either a sum of the two inputs to the headphones output, or an external stereo cue mix (such as a stereo mix feed from an interface) via two TRS Jack inputs on the rear of the unit

Optional stereo 192 kHz analog-to-digital conversion card utilizes cutting-edge conversion technology and Focusrite analog circuitry to deliver the highest A/D performance with a dynamic range of 119 dB

Dedicated insert point allows the user to place extra processing such as an EQ or compressor, between the preamplifier or DI and the optional converter

Includes Brainworx bx_console Focusrite SC channel-strip plug-in, a stellar digital emulation of the legendary and rare Focusrite Studio Console

Focusrite ISA ONE Specs

Number of Channels Single
Inputs 1 x XLR Microphone
1 x XLR Line
1 x 1/4" TRS phone Line
1 x 1/4" TRS phone Instrument
1 x 1/4" TRS phone External Input
1 x 1/4" TRS phone Cue Left
1 x 1/4" TRS phone Cue Right
1 x 1/4" TRS phone Return

Output 1 x XLR Line
1 x XLR DI
1 x 1/4" TS DI Thru
1 x 1/4" TRS phone Send
1 x 1/4" TRS phone Headphone
Phantom Power 48V
Multi Function No
Gain Range Mic: 0 to 60 dB in 10 dB steps with 20 dB of variable gain
Line: -20 to +10 dB in 10 dB steps with 20 dB of variable gain
Maximum Output Level Not specified by manufacturer
Frequency Response 16Hz to 118kHz, -3.0dB at maximum gain
Noise Mic SNR: 106 dB
Line SNR: 120 dB
Dimensions 8.7 x 10 | 11.4 x 4.1" / 22 x 25.4 | 29 x 10.4 cm
Weight 8.6 lb / 3.9 kg
Packaging Info
Package Weight 12.9 lb
Box Dimensions (LxWxH) 16.2 x 15.5 x 9.3"