

Marantz LINK10N/N1B

Šifra: 19102

Kategorija proizvoda: Network Plejeri

Proizvođač: Marantz

Cena: 1.500.000,00 rsd



General

Unit (W × H × D mm): 440 × 192 × 472 (with antenna)

Cabinet Size: 440 × 192 × 422

Net weight: 33.3kg

Packaging Dimensions (W × H × D mm): 600 × 379 × 540

Packaging gross weight: 38.7g

Carton Color: 1 Color (Material color: Brown Printing: Black)

Panel Color: Black / Marantz Champagne

Front (Center) Pane: Aluminum

Back-shell: Aluminum

Front panel illumination: Yes (All sides, Dimmer)

Side cover: Aluminum (Thickness: Max 15.8mm)

Top cover (Center) ventilation hole material: No

Interior illumination: No

Rear Panel: Triple layer Copper-plated

Chassis Material: Copper-plated

Bottom Layer / Bottom plate: Copper-plated

Volume Knob: Solid aluminum (Bearing construction)

Input Selector: Solid aluminum (Bearing construction)

Foot: Solid aluminum with Copper

Audio

Frequency Response: PCM 2Hz-50kHz (-3dB)

Harmonic distortion: PCM 0.0004%

S/N: PCM 0.0004%

Dynamic range: PCM 0.0004%

Line Output Level:

- UNBALANCED : 2.0Vrms
- BALANCED : 4.0Vrms

Headphone Output Level: 130mW / 32 ohms

Frequency Response (analog input): 5 Hz-100 kHz (+0dB/-3 dB)

Harmonic distortion (analog input): 0.001% (20Hz-20kHz)

S/N:

- PHONO (MC) : 76dB
- HONO (MM) : 88dB
- BALANCED : 122dB
- LINE : 122dB

Phono Input sensitivity:

- MM : 8mV

- MC : 80mV

Phono Input impedance:

- MC Low : 32 ohms
- MC Mid : 100 ohms
- MC High : 390 ohms
- MM : 39 kohms

Power Consumption:

- 7W
- Less than 0.3W (at Standby)
- Less than 2W (at Network Control On: Bluetooth, Ethernet, Wi-Fi, USB)

Audio Feature

Output Circuit: New HDAM

Power Transformer: Toroidal

Pre Amplifier Circuit:

- New HDAM High Grade
- Full balance

Volume:

- Electric (MUSES 72323)
- Variable gain

Bass / Treble / Mid / Balance Control: Yes / Yes / No / Yes

Type of Tone Control: Electric

Headphone Circuit: Discrete

H/P Amp Gain Setting: Yes (Low / Mid / High)

H/P On.Off Setting: H/P Off automatically, when in use

DAC Circuit: New MMM-Conversion

Dither: MMM-Stream (Dither 1, 2, Off)

Noise Shaper:

- MMM-Stream
- Balanced, Natural, Dynamic Music, Dynamic Voice)

Digital Filter:

- MMM-Stream
- Filter 1, 2 Selectable

Jitter Reducer: Yes

DAC Master Clock Design (No Support for Network Playback): Yes

Asynchronous mode (for USB-B input): Yes

Isolator (for USB-B input): Yes (Complete Isolation System Duo)

Fixed Analog Output (RCA):

- Cinch × 1
- Thick nickel plated independent terminals

Pre / Variable Audio Output (RCA):

- Cinch × 1
- Thick nickel plated independent terminals

Fixed Balanced XLR Output: Yes (1 Pair)

Pre/ Variable Balanced XLR Output: Yes (1 Pair)

RCA Input:

- Cinch × 1
- Thick nickel plated independent terminals

Balanced XLR Input: Yes (1 Pair)

Phono input:

- Yes (MM / MC)
- Marantz Musical Premium Phono EQ w/ Selectable MC impedance (3 position)
- Thick nickel plated independent terminals

Optical input / output (Maximum Support):

- 2 / 1 (on/off switchable)
- 44.1 kHz - 192 kHz

Coaxial input / output (Maximum Support):

- 1 / 1 (on/off switchable)
- 44.1 kHz - 192 kHz

HDMI input / output: No / Yes (ARC)

Headphone Output: Yes (Φ6.3 ×1)

Subwoofer: Yes with LP filter adjustable

Easy to Use

App: HEOS app

Remote Controller: 10 series universal Remote control

Front Panel Display: New HD TFT Color Display

Display Language

- N: (English/ German/ French/ Italian/ Dutch/ Spanish/ Swedish/ Polish/ Russian)
- U: (English/ French/ Spanish)
- K: (Simplified Chinese/English)
- F: (Japanese/ English)

Dimmer for Front Display: 20 steps

Level meter: No

Volume Display: 0 -100 / 0.5 step (defalut)-infinity/-99.5dB - 0dB / 0.5 step switchable

Voice Assistant:

- Apple Siri
- Google Assistant

Control with App via Network Player (Use Remote Control Bus): No

External Amp Control with App (Use Remote Control Bus): Yes

Synchronously turn on amplifier and switch the input (Use Remote Control Bus): Yes

HDMI CEC: Yes

Remote Controller: RC004PMND

Battery: Yes (AAA ×2)

Power Cord: Yes (ALL region : Audio Grade : OFC)

Other:

- Stereo RCA Cable ×1
- Remote connector cable ×1
- CoA card