Firma: Player Plus doo
Adresa: Svetogorska 9
Telefon: +381 11 3347 442
Fax: +381 11 3347 615
PIB: 106966344
E-mail: porudzbine@player.rs

ARCAM RADIA A25+ - Integrisano pojačalo



Šifra: 20822
Kategorija prozivoda: Integrisana Pojačala
Proizvođač: ARCAM

Cena: 179.880,00 rsd

Continuous power output (0.5% THD), per channel
2 channels driven, 20Hz - 20kHz, 8Ω 100W
2 channels driven, 1kHz, 4Ω 165W
Harmonic distortion, 80% power, 8Ω at 1kHz 0.002%

Analogue Inputs
Number of inputs 3 (RCA pairs)
Signal/noise ratio (A-wtd, ref. 50W, 1V input) 106dB
Frequency response 20Hz—20kHz ± 0.2dB

Phono (MM) Input
Input impedance 47kΩ + 100pF
Frequency response (ref. RIAA curve) 20Hz—20kHz ± 1dB

Digital Inputs
Supported Sample Rates (kHz)
USB-C Only 384, 352.8, 192, 176.4, 96, 88.2, 48, 44.1
Other digital inputs 192, 176.4, 96, 88.2, 48, 44.1

Bit depths (bit) 32, 24, 16
Frequency response (filter 1) 20Hz—20kHz ± 0.2dB
Signal/noise ratio (A-wtd, ref. 50W, 0dBFS) 109dB

Headphone Output
Maximum output level (RMS) into 32Ω/300Ω 2.5V/5V
Load range 16Ω - 2kΩ

Wireless Specifications
Bluetooth Version - 5.4; A2DP Sink/Source, AVRCP, BLE, SBC, AAC, aptX, aptX HD and aptX Lossless, LE Audio, Auracast
Bluetooth Transmitter Frequency and Power - 2,400 MHz to 2,483.5 MHz: <20dBm

General
Mains voltage 100V or 110–120V or 220–240V, 50–60Hz
Power consumption (maximum) 500W
Power consumption (standby) <0.5W
Dimensions W x D (including speaker terminals) x H (including feet) 431 x 344 x 83mm

Weight (net) 9kg
Weight (packed) 12kg

Supplied accessories
Mains lead(s)
Remote control with 2 x AAA batteries
Quick Start Guide
Important Safety Instructions

Cene su informativnog karaktera. Prodavac ne odgovara za tačnost cena iskazanih na sajtu, zadržava pravo izmena cena. Ponudu za ostale artikle, informacije o stanju lagera i aktuelnim cenama možete dobiti na upit. Plaćanje se isključivo vrši virmanski - bezgotovinski.