

## EVE AUDIO TS108 - Sabvufer

Šifra: 10351  
Kategorija proizvoda: Subwoofer Monitori  
Proizvođač: EVE Audio

**Cena: 71.880,00 rsd**

This guarantees a frequency response of down to 33Hz (on the lower end), up to 300Hz, for a maximum output power of 105 dB (SPL @ 1m).

The included remote control will let you adjust not only the subwoofer's volume but also the complete stereo system's volume while sitting comfortably in your sweet spot.

All in all, the ThunderStorm subwoofers will make any system sound better and more complete.

As with every other EVE Audio subwoofer, you get balanced XLR In- and Outputs (Stereo In and Out, LFE In, LFE/Sub Out) for greater convenience.

### Passive Radiator

The particularity of our extremely powerful and accurate subwoofer resides in the passive radiator used that replaces the common bass reflex tube. With this design all audible noise due to air turbulences disappear completely.

Unwanted disturbing pipe resonances (at  $\lambda/2$  and multiples) are eliminated, which are unavoidable when applying the principle of a two-sided pipe opening (bass reflex port). The suspension of the passive radiator has a restoring force underneath its tuning frequency and reduces inaudible excursions in the subsonic range. This in turn results in reduced intermodulation distortion in the working range.

The passive radiator allows a particularly low tuning or lower cut-off frequency in a very compact cabinet.

### Product TS108

Description Subwoofer  
Dimensions (WxHxD) [mm] 280 x 415 x 365  
Dimensions (WxHxD) ["] 11.02 x 16.34 x 14.37  
Free-field frequency range (-3dB) 33Hz - 300Hz  
Woofers 195mm/8"  
Maximum SPL @ 1m 105dB  
Number of amplifiers 1  
Output power (woofers) 150W  
Protection limiter  
Settings  
System volume (Satellite & Sub) -inf. - +6dB  
Subwoofer volume -inf. - +6dB  
LED brightness setting  
Level-lock dip switch  
Filter-lock dip switch  
Input level dip switch +7dBu/+22dBu  
Phase inversion 0°/180°  
Switchable Satellite filter flat/80Hz

### EVE AUDIO TS108 - Sabvufer

Every ThunderStorm subwoofer has detailed controls like switchable satellite filters (full range and 80Hz), phase switch controls (0°, 180°). and variable subwoofer filter frequencies (60....140Hz) to let you tailor and adjust your ThunderStorm to your specific room.

The TS108 model features a very efficient 150W PWM amplifier that drives a proprietary 8" woofer.

**Tech  
Talk**

Variable Subwoofer filter 60Hz-140Hz + LFE

Remote control Sys. & Sub. Vol.

Connectors

XLR in left (impedance) (10k)

XLR in right (impedance) (10k)

XLR in LFE (impedance) (10k)

XLR out satellite left (impedance) (10k)

XLR out satellite right (impedance) (10k)

XLR out (LFE) (impedance) (10k)

Power consumption

Standby < 1W

Full output 170VA

Misc.

Weight kg/lb. 11.5 / 25.3