

MARTIN WISMAN MXD 3000

Šifra: 07085

Kategorija proizvoda: Višezonske Miksete

Proizvođač: Martin Wisman

Cena: 23.880,00 rsd



6 Zones Mixer pre amplifier

- * Mixer with 6 zone speaker selector for source selection and zone control
- * Build-in mic and recorder for easy voice message recording and storage
- * 3 audio sources direct selection on front panels
- * 6 zone selection buttons on front panel
- * 6 zone paging console work together with the mixer through RJ45 port for remote control and announcement
- * Mic input by XLR type with phantom power and gain control
- * 3 aux inputs for tape, CD and tuner
- * Built-in chime, whose remote trigger and volume is provided
- * 3 voice messages broadcast in continuous and once modes
- * 3 channel pre outputs: music, music/page and page
- * 6 zone line outputs for power amplifier
- * Volume control is provided for mic, music, mater, record and message broadcast, plus bass and treble tone control
- * Indications include zone selector, source selector, record state, power and output level meters.
- * 4 levels of priority from high to low: remote paging console, Mic1, chime, pre-recorded message broadcast.

Specifications

Model	MXD-3000
CONSOLE INPUT	
Sensitivity	±5 mV/600?, ±500mV/10K?
S/N Ratio	>68dB
Frequency Response	50Hz~17KHz(+1, -3dB)
MIRCOPHONE INPUT	
Sensitivity	±5 mV/600?, ±500mV/10K?
S/N Ratio	>68dB
Frequency Response	50Hz~17KHz(-3dB)
Phantom Power	+48V
3 AUXILIARY INPUTS	
Tuner and Tape Input Sensitivity/Impedance	200mV/47?
CD Input Sensitivity/Impedance	500mV/47?
S/N Ratio	>90dB
Frequency Response	20Hz~20KHz(+1, -3dB)
CONTROL	
Bass	±12dB at 100Hz
Treble	±12dB at 10KHz
Chime	2 tone active for contact free in priority and BGM
Normal Distortion	>0.05%
OPERATING CONDITION	
Power Supply	~110V/60Hz or ~230V/50Hz & DC 24V
Dimensions	484x303x88mm
Weight	6.58Kg
Max number of paging console	6

Rear Panel

Image not found or type unknown



