

QSC RMX 1450 - Razglasno pojačalo

QSC RMX 1450 - Razglasno pojačalo

**RMX
1450**

Šifra: 06329
 Kategorija proizvoda: Razglasna Pojačala
 Proizvođač: QSC

Cena: 95.880,00 rsd

The power supply is the heart of an amplifier, converting raw AC power from the wall to clean DC for the audio circuitry. The RMX uses a powerful high-current toroidal transformer and ample filter capacitance to ensure generous energy reserves. This makes a critical difference in sound quality, allowing the amp to effortlessly punch out high level transients, even when driving abusive 2-ohm

speaker loads.

Superior Performance

RMX amplifiers deliver true studio-quality sound. A full complementary output circuit using the highest-grade linear output devices delivers ultra-low distortion (<0.05% THD) and a ruler-flat frequency response. SMT (Surface Mount Technology) triples small-signal component density, enabling us to pack up to 2400 watts of power in a chassis only 2 rack spaces and less than 16" deep. And unlike other designs, RMX output devices are direct-mounted to the heat sink for optimum thermal coupling and cooling.

Features

- Independent defeatable clip limiters reduce distortion without sacrificing peak performance.
- Selectable low-frequency filters boost system response, protect speakers, and ensure low-end tightness by more precisely matching the amplifier's range to the loudspeakers.
- Barrier strip, XLR, and 1/4" balanced inputs plus Speakon and binding post outputs provide easy connections.
- Low-noise variable speed fans with rear-to-front air flow keep amplifiers and racks cool.

SPECIFICATIONS	RMX 1450
STEREO MODE (Both Channels Driven)	
8 ohms FTC 20 Hz - 20 kHz, 0.1% THD EIA 1 kHz, 0.1% THD	260 W 280 W
4 ohms FTC 20 Hz - 20 kHz, 0.1% THD EIA 1 kHz, 0.1% THD	400 W 450 W
2 ohms EIA 1 kHz, 1% THD	700 W
BRIDGE MONO MODE	
8 ohms FTC 20 Hz - 20 kHz, 0.1% THD EIA 1 kHz, 0.1% THD	800 W 900 W
4 ohms EIA 1 kHz, 1% THD	1400 W
Signal to Noise, 20 Hz-20 kHz	100 dB
Distortion (SMPTE-IM)	Less than 0.01%
Input Sensitivity @ 8 ohms	1.15V (+3.4 dBu)

Voltage Gain		40x (32 dB)	
Output Circuitry		AB	
Power Requirements 1/8 power pink noise at 4 ohms *		6A	
ALL MODELS			
Distortion (Typical) 20 Hz - 20 kHz: 10 dB below rated power 1.0 kHz and below: full rated power		Less than 0.03% THD, 4 and 8 ohms Less than 0.03% THD, 4 and 8 ohms	
Frequency Response		20 Hz-20 kHz, ± 1 dB -3 dB points: 5 Hz - 50 kHz	
Damping Factor, 1 kHz and below		Greater than 300 at 8 ohms	
Input Impedance		10k ohms unbalanced, 20k ohms balanced	
Input Clipping		10 Vrms (+22 dB)	
Cooling		Continuously variable-speed fan, rear-to-front air flow	
Connectors, each channel		Input: Active balanced; barrier strip, XLR and 1/4" (6.3mm) TRS tip and XLR (pin 2 positive) Output: touch-proof binding posts and Neutrik® Speakon®	
Controls		Front: AC switch, Ch. 1 and Ch. 2 gain knobs Rear: 10-position DIP switch	
Indicators		Power-On: Green LED Signal: Yellow LED (1 per channel) Clip: Red LED (1 per channel)	
Amplifier Protection		Stable into reactive or mismatched loads	
Load Protection		On/off muting, AC coupling (850, 1450), triac crowbar (1850HD, 2450)	
Power Requirements		100, 120, 230 VAC, 50-60 Hz	
Dimensions		19" (48.3 cm) rack mounting, 3.5" (8.9 cm) tall (2 RU), 15.9" (40 cm) deep (rack mounting to rear support ears)	