Firma: Player Plus doo
Adresa: Svetogorska 9
Telefon: +381 11 3347 442
Fax: +381 11 3347 615
PIB: 106966344
E-mail: porudzbine@player.rs

Audiolab D7 Silver - DAC

Šifra: 19992
Kategorija prozivoda: Dock-ovi
Proizvođač: Audiolab



Cena: 47.880,00 rsd

Model: D7
General Description: DAC
Design Philosophy and Core Technology:
• ES9038Q2M 32-bit DAC
• MQA Full decoder (PC USB, Coax / Optical)
• OLED Display
• Bluetooth 5.1 (aptX / aptX HD) streaming
• Dedicated Current-Feedback Headphone Amp
• Supports playing USB memory device (MP3 / WMA / APE / AAC / WAV / FLAC)
• USB Firmware Upgrade
Inputs:
• 2 x SPDIF (Coax), 2 x SPDIF (Optical), 1 x PC USB (USB B),
• 1 x USB HDD (USB A), 1 x Bluetooth (aptX / aptX HD)
Outputs: 1 x RCA, 1 x XLR, 1 x Headphone, 2 x 12V Trigger, 1 x Optical, 1 x Coax
Sampling Frequency:
• Optical/Coaxial: 44.1kHz–192kHz
• USB HDD: 44.1kHz–96kHz
• PC USB: 44.1kHz–768kHz (PCM) / DSD64, DSD128, DSD256, DSD512

DAC
D to A Converter: ES9038Q2M
Output Level (0dBFS, 1kHz): 2.05Vrms (RCA), 4.1Vrms (XLR)
Total Harmonic Distortion (THD): < 0.001% (1KHz @ 0dBFS)
Frequency Response: 20Hz-20kHz (+/-0.2dB)
Output Impedance: 120 ohm
Max. Sampling Frequency:
• USB HDD: 96KHz
• Optical,Coaxial: 192KHz
• PC USB: PCM768kHz, DSD512
Signal-to-noise Ratio (S/N):
> 115dB (A-weighted, RCA)
> 117dB (A-weighted, XLR)

Headphone Amplifier
Total Harmonic Distortion(THD): < 0.01% (1kHz, 50mW)
Output Impedance: 2.35 ohm
Load Impedance: 20-600 ohm

General
Standby Power Consumption: <0.5W
Net Weight: 1.42 kg
Gross Weight: 2.2 kg
Dimensions (mm) (W x H x D): L: 180 x W: 208 x H: 56mm
Carton Size (mm) (W x H x D): L: 290 x W: 325 x H: 85mm

Finish
Power Requirements (depending on region):
• 220-240V ~ 50/60Hz
• 100-120V ~ 50/60Hz
Standard Accessories: Power adapter, Remote Control, User Manual, etc.

Cene su informativnog karaktera. Prodavac ne odgovara za tačnost cena iskazanih na sajtu, zadržava pravo izmena cena. Ponudu za ostale artikle, informacije o stanju lagera i aktuelnim cenama možete dobiti na upit. Plaćanje se isključivo vrši virmanski - bezgotovinski.