logo
Image not found or type unknown

Firma: Player Plus doo
Adresa: Svetogorska 9
Telefon: +381 11 3347 442
Fax: +381 11 3347 615
PIB: 106966344
E-mail: porudzbine@player.rs

ZOOM B3n - Procesor za bas gitaru
Image not found or type unknown

ZOOM B3n - Procesor za bas gitaru

Šifra: 12465
Kategorija prozivoda: Procesori
Proizvođač: ZOOM

Cena: 22.680,00 rsd

Three footswitches allow you to initiate effects, which are all editable via three separate LCD screens, each of which boasts four dedicated parameter controls, which change depending on the effect you choose. At the bottom of the pedal are three more foot controls: two scroll pedals for cycling through banks, as well as a third control for tap-tempo and tuner regulation. An 80-second phrase looper is also available to you, for all your looping needs.

The pedal provides both instrument and auxiliary inputs, and an output section which gives you a mono 1/4" output and a stereo 1/4" output, useful for monitoring through headphones or implementing stereo effects. A controller input will allow you to hook in compatible expression control pedals, such as the FP02M.

Included Software
The included Zoom Guitar Lab software for Mac and Windows enables you to manage patches, download new effects, and activate different amp/cabinet emulators. It includes a Patch Manager for effects chains, as well as an Effects Manager with a simple graphic user interface. This provides point-and-click control over re-naming or re-ordering your custom patches.
Features at a Glance
67 high-quality stompbox DSP effects
5 new amp emulators, plus 5 cabinet emulators
Included ZOOM Guitar Lab Mac/Windows software for allows downloading of additional effects and patches
Use up to 7 effects simultaneously, chained together in any order
3 stompbox switches allow effects to instantly be brought in and out
Stereo/mono looper allows recording of up to 80 seconds of phrase recording
3 independent editing displays
Onboard chromatic tuner with dedicated footswitch supports all standard bass tunings including open and drop-tunings (tuner center-range of 435 to 445 Hz)
68 built-in rhythm patterns which can be used in conjunction with the looper
Tap Tempo with dedicated footswitch
Auxiliary stereo input jack for connection of smartphones and music players
Dual output jacks for connection to bass amps and mono/stereo PA systems
Dedicated stereo headphone output jack
Control input for ZOOM FP02M external expression pedal

Effects Types 80x
Simultaneous Effects Up to 7x
User Banks 150 banks and patches
Sampling Frequency 44.1 kHz
AD/DA Conversion 24-bit with 128x oversampling
Signal Processing 32-bit
Frequency Characteristics 20 Hz to 20 kHz, +1 dB, -3 dB (10-kOhm load)
LCD Display 3x 128 x 32 dot-matrix
Input Connections 1 x 1/4" phone jack
1 x Stereo 3.5 mm mini jack
1 x Zoom FP02M Control input

Input Level 1/4" phone: -20 dBu
3.5 mm mini: -10 dBu
Input Impedance 1/4" phone: 470 kOhms (line)
3.5 mm: 10 kOhms (line)
Output Connections 1 x 1/4" phone jack, mono
1 x 1/4" phone jack, stereo (combined line / headphone)
Output Level Output R: Line +5 dBm (load impedance of 10 kOhms or more)
Output L: Line +5 dBm (load impedance of 10 kOhms or more); headphones 15 mW + 15 mW into 32-Ohm load
EIN -119 dBu
Noise Floor -100 dBu
Power Zoom AD-16 AC adapter: 9 VDC (center minus plug), 500 mA
USB USB MIDI, USB Micro-B
Dimensions 7.1 x 9.2 x 2.3" / 18.1 x 23.4 x 5.8 cm
Weight 2.8 lb / 1.3 kg
Packaging Info
Package Weight 3.69 lb
Box Dimensions (LxWxH) 12.95 x 8.05 x 3.15"

Cene su informativnog karaktera. Prodavac ne odgovara za tačnost cena iskazanih na sajtu, zadržava pravo izmena cena. Ponudu za ostale artikle, informacije o stanju lagera i aktuelnim cenama možete dobiti na upit. Plaćanje se isključivo vrši virmanski - bezgotovinski.