**logo**e not found or type unknown

Firma: Player Plus doo Adresa: Svetogorska 9 Telefon: +381 11 3347 442 Fax: +381 11 3347 615

Fax: +381 11 334 PIB: 106966344

E-mail: porudzbine@player.rs

Biampot Aparti CMe5. Ekhov Plafonski zvučnik

## Biamp - Apart CM 5EH - Plafonski zvučnik

Šifra: 8192

Kategorija prozivoda: Plafonski Zvučnici

Proizvođač: Biamp - Apart

Cena: 2.880,00 rsd

Speaker type: 5 inch coated paper cone

Rated power RMS: 6 W - 3 W @ 100 V

Music power Lo-Z: 30 W

Frequency range: 100 - 18000 Hz

spl 1W/1m: Dispersion at 1 kHz 160° / Dispersion at 4

Rated

Nomi Sensi

Chass

Grille

Fixing

Dime

Moun

Speal

kHz 90°

Chassis type: plastic Removable grille: Yes IP classification: 54

Dimensions cutout Ø: 160 mm

Total depth including mounting frame and grille: 50 mm

The new CM5EH is a humidity resistant version of the popular CM5E in-wall speaker and is suited for bathrooms, kitchens, cool cells or other humid zones. In principle, this product is pretty similar to the Apart CM5E with exception to the cone and grille material. The newest version has a plastic grille whose outlook will surprise you.

Most humidity resistant speakers have a somewhat awkward appearance, but the CM5EH has the same stylish design like the other Apart ceiling speakers. This means the loudspeaker has a higher optical integration and will keep consistency in buildings.

The loudspeaker is very easy to install, due to the simple mounting system with 2 hidden spring loaded clamps. You just need to open the clamps with your hands, carefully slide the speaker in place and release the clamps while positioning the speaker in the middle of the cut-out. This easy way of installation doesn't require any tools and saves the installer precious time!

The CM5EH is a modern and very competitive built-in loudspeaker, featuring a 100 Volt speaker line transformer as well as a direct 8 ohms connection, allowing you to connect up to 2 speakers in parallel per  $4\Omega$  stable amplifier channel. For 100 Volt use, the CM5EH is equipped with a high quality 3/6 Watt 100 Volt transformer.

Image not found or type unknown