

ART PRO AUDIO MX822CE



Šifra: 10271

Kategorija proizvoda: Pa Rack Ostalo

Proizvođač: ART

Cena: 19.080,00 rsd

- Eight stereo/mono input channels with individual level, pan and effects send controls
 - External effects loop with independent send and return controls
 - Front panel 1/4-inch stereo (TRS) headphone jack with amplifier and independent level control for output monitoring
 - Switchable balanced microphone XLR or 1/4-inch inputs on Channel One
 - Switchable low noise +48V phantom power for microphone input
 - Separate green and red LED signal and clip indicators for each input channel
 - Six level left and right main output metering including clip indicators
 - Balanced left and right XLR main outputs
 - Multiple units may be chained together for additional inputs
 - Rugged 1U rack mount steel case
- 8-Channel Stereo Mixer with Effects Loop**

Input Connections	XLR-F balanced (MIC) 1/4" TRS unbalanced (Ch1-Ch8, Effects Return) 1/4" TRS stereo unbalanced (EFX Buss, Main Expand)
Output Connections	XLR-M balanced (Main) 1/4" TRS unbalanced (Effectss Send) 1/4" TRS stereo unbalanced (Monitor, Main Expand, Headphone)
Input Impedance	1k Ohms (MIC), 5k Ohms (Ch1-Ch8)
Output Impedance	
Total Harmonic Distortion	<0.01% @ 1kHz
Signal to Noise Ratio	> 90dB typical (Ref 0dBu)
Maximum Input Level	-19dBu (MIC), +24dBu (Ch1-8)
Maximum Output Level	+24dBu (Main), +18dBu (Monitor, Effects Send)
Maximum Gain	+60dB (MIC), +14dB (Ch1-8)
Phantom Power	Switch Selectable, +48V DC, filtered, current limited

Power Requirements	USA - 95 to 125 VAC, 50-60 Hz Export units configured for country of destination
Dimensions	1.75"H x 19"W x 6"D (44.5mm x 483mm x 152mm)
Weight	6.5 lbs (2.95 kg)