1090e not found or type unknown

Firma: Player Plus doo Adresa: Svetogorska 9 Telefon: +381 11 3347 442 Fax: +381 11 3347 615

PIB: 106966344

E-mail: porudzbine@player.rs

KEF KW1 TX/RX System - Bežični predajnik/prijemnik

Šifra: 14863

Kategorija prozivoda: Ostalo

Proizvođač: KEF

Cena: 27.480,00 rsd

KEG-KW1oTX/RX\SystemwnBežični predajnik/prijemnik

Comprising a discreet transmitter and receiver, KEF KW1 works with the KUBE 8b, 10b, 12b, KC62 and KF92 subwoofers. It allows KEF subs to be optimally placed, and not limited by cables. High-quality wireless transmission delivers every ounce of detail and impact from your favourite films and music.

Performance with convenience

KW1 operates in the high-bandwidth 5GHz band and delivers audio up to 24bit/48kHz. The transmitter is powered by USB, while the receiver is powered directly by the subs expansion port. Pairing is intuitive and highly stable, while a range of up to 30m (line of sight) makes placement easy. KW1 is also perfectly suited for use with KEF's LSX, LS50 Wireless and LS50 Wireless II.

Features

LOSSLESS AUDIO

5.2 & 5.8GHz selectable digital wireless link for near lossless audio

ADVANCED ALGORITHM

Advanced RF Selection Algorithm

WIDE RANGE
Up to 15 metre (30M/ 100 ft line of sight) operational distance between transmitter and receiver
LOW LATENCY
Designed with latency of <17ms
HIGH PERFORMANCE
24-bit 48KHz high resolution audio for pristine performance
The Details
SPECIFICATIONS
MODEL
KW1
RADIO FREQUENCY
5.2GHz and 5.8GHz
SAMPLING RATE
24bit, 48KHz

LINK DISTANCE
Max 100ft (Line of Sight)
FREQUENCY RESPONSE
20Hz-22kHz
SIGNAL-TO-NOISE RATIO
>80dB
TRANSMITTER POWER INPUT
5V DC 1A
AUDIO OUTPUT LEVEL
2V
TRANSMITTER INPUT LEVEL
2V
TOTAL HARMONIC DISTORTION
typ90dB

LATENCY

<17ms

DIMENSION HXWXD

Transmitter

21.4 x 72 x 79.5mm

Receiver

27 x 37 x 72mm

DOWNLOADS

KW1 Info Sheet KW1 TX/RX System Manual

KW1 RX Receiver Manual