lage not found or type unknown

Firma: Player Plus doo Adresa: Svetogorska 9 Telefon: +381 11 3347 442 Fax: +381 11 3347 615

PIB: 106966344

E-mail: porudzbine@player.rs

PRO-JECT Phono Box E BT Black Gramofonsko Pretpojačalo sa Bluetooth transmisijom

Šifra: 15531

Kategorija prozivoda: Gramofonska Pretpojačala

Proizvođač: Pro-Ject

Cena: 16.680,00 rsd

PROJECTO Phono Box டக்கா Black Gramofonsko Pretpoja entry

level phono stage has been highly requested by the aspiring and rising audiophile. After the big success of our VT-E BT we decided to create a phono preamplifier that turns any turntable (with moving magnet cartridge) into a modern BT streamer. Phono Box E BT offers two separate inputs, one phono and one line level input, as well as two separate outputs. It can be used as an ordinary MM phono stage that connects to any hifi amplifier via its line level ouput (3.5mm jack) or it can be used as a BT streamer. It takes any provided analogue input signal, converts it and sends digital audio to any BT

receiver within a 10m range. Those devices could be either BT headphones, speakers or any other BT receiver. The super-fast pairing is the icing on the cake and makes sure that listening to your LPs will be as painless and quick as possible.

The housing is shielded with a metal interior which protects the unit against vibrations and radio frequency interferences, which guarantees an undisturbed listening experience.

Phono Box E BT is the perfect companion for all modern audiophiles who want to enjoy their vinyl hobby with the comfort of wireless streaming!

Features

Wireless BT streaming from line or phono sources

2 Inputs: 1 Phono and 1 Line Input

Suitable for MM cartridges Precise RIAA equalisation

Use analogue RCA & BT output simultaneously

Low noise circuitry

Internal metal shielding

Gold-plated RCA connectors

Outboard power supply included

Colour options: black or white

Phono capacitance	100 pF
Gain phono	34 dB
Inputs	1 Phono (RCA), 1 Line In (3.5 mm)
Outputs	1 Line Out (3.5 mm), 1 Bluetooth
Noise floor	74 dB
THD	< 0,02% at 1kHz
Phono/Line in max. input voltage	800mV
RIAA equalisation curve accuracy	within 0.5 dB/20 Hz - 20 kHz
вт	V2.1, EDR
outboard power supply	18 V/500 mA DC, suitable for your country's mains supply
Power consumption	200 mA DC
Dimensions W x H x D (D with sockets)	120 x 32 x 100 (106) mm
Weight	280 g without power supply

