

## AKG C 516 ML

Šifra: 3371  
Kategorija proizvoda: Lavalier i Ostali Mikrofoni  
Proizvođač: AKG

Cena: **17.640,00 rsd.**



Cardioid instrument microphone with miniature mounting bracket

High mechanical-noise attenuation

Detachable microphone cable

Includ  
pocke  
Ideal  
keybo

Lightweight cardioid miniature microphone for use on accordions, guitar speakers, piano and keyboard/organ cabinets. The included screws and double-sided, solvent-free adhesive pads make it easy to install the microphone on your instrument or amp exactly where you need it.

Using two C 516 MLs (one on the bass and one on the treble side) and an optional B 29 L battery power supply is an ideal way to mic up an accordion.

The C 516 ML is the only version available and can be used with the B 29 L battery power supply, AKG WMS Series bodypack transmitters, or the MPA V L adapter for external phantom powering. The unique adapter plate A 400 allows easy attachment of the AKG pocket transmitters.

<b>Polar pattern</b>	cardioid
<b>Frequency range</b>	60 Hz to 20 kHz
<b>Sensitivity</b>	5 mV/Pa (-46 dBV)
<b>Max. SPL</b>	130/132 dB SPL (bei k = 1 %/3 %)
<b>Equivalent noise level</b>	31 dB(A)
<b>Signal/noise ratio (A-weighted)</b>	63 dB
<b>Impedance</b>	<= 200 ohms
<b>Recommended load impedance</b>	>= 2000 ohms
<b>Powering</b>	<= 2 mA
<b>Power requirement</b>	B 29 L battery power supply, MPA V L phantom adapter, AKG WMS bodypack transmitters

<b>Connector</b>	3-pin mini XLR
<b>Cable</b>	1.5 m (5 ft.)
<b>Finish</b>	matte black
<b>Dimensions</b>	length: 235 mm (9.3 in.) (microphone only); max. width: 47 mm (1.9 in.)
<b>Net weight</b>	46 g (1.6 oz.) (microphone and cable)
<b>Shipping weight</b>	320 g (11.3 oz.)