

CASIO CT-X5000 - Klavijatura Aranđer

Šifra: 12678
Kategorija proizvoda: Aranžeri
Proizvođač: CASIO

Cena: 51.480,00 rsd

User tones: 100
Functions: Layer, Split
Digital effects
Reverb: 32 types, off
Chorus: 16 types, tone
Delay: 20 types, tone
DSP: 100 types, DSP tones
Master effects
Equalizer (10 Presets), 4-band user equalizer
External input effects
Center cancel (vocal cut) for input from the audio in jack
Metronome
Beats per measure: 0 (accented tone off), 1 to 16
Tempo range: 20 to 255
Song bank
Demo song: 3
Built-in songs: 30
User-recorded songs: 10
USB Flash Drive SMF files
Playback of standard MIDI files (SMF format 01/1), CASIO MIDI files (CMF format) on a USB flash drive is supported.
USB audio playback
Playback of audio files on a USB flash drive is supported.
Supported file formats: WAV, 44,1 kHz 16 Bit
Other functions: Center cancel (vocal cut)
Auto accompaniment
Built-in rhythms: 235
User rhythms: 50
Music presets
310
One touch presets
235
Phrase Pads
Number of pads: 4
User Phrases: 100 (4 phrases x 25 pads)
Editing mode: Copy, delete, phrase editing
Mixer functions
Affected parts: Sound source parts, microphone input part
Parameters: Part on/off, volume, pan reverb send, chorus send, delay send
Registration
128 setups (8 setups x 16 banks), registration sequence
Tone editing

CASIO CT-X5000 - Klavijatura Aranđer

Keyboard
61 keys
Touch response
3 types, off
Maximum Polyphony
64 notes (32 for certain tones)
Tones
Sound Source: AiX
Built-in tones: 800

Preset tone editing, DSP editing. Memory for storage of edited tones (up to 100)

Internal rhythm editing

New rhythm creation, rhythm editing Memory for storage of created/edited rhythms (up to 100)

MIDI recorder

Real-time recording, playback

Keyboard play: 10 songs, 17 tracks (1 system track, 16 solo tracks)

Memory capacity: approximately 40.000 notes (per song)

Editing mode: Song editing, track editing, event editing, step input

Other functions: Overdubbing, punch-in recording

Controllers

Pitch bend wheel, SUSTAIN button, PORTAMENTO button, MODULATION/ASSIGNALE button

Other functions

Transpose: ± 1 octave (-12 to 0 to + 12 semitones)

Octave shift: Upper 1/ Upper 2/ Lower 1/ Lower 2, ± 3 octaves

Tuning: A4 = 415,5 to 465,9 Hz (initial default: 440,0 Hz)

Part coarse tune: For each keyboard part, ± 2 octaves (-24 to 0 to + 24 semitones)

Part fine tune: For each keyboard part, ± 99 cents

Preset scales: 17 preset scales, scale fine tuning

Auto harmonize: 12 types

Arpeggiator: 150 types

MIDI

16-multi-timbre received, GM Level 1 standard

Inputs/Outputs

USB flash drive port: Type A

USB port: Type B

Pedal jack 1: Standard jack (sustain, sostenuto, soft, rhythm)

Pedal jack 2, expression jack: Standard jack (expressio jack)

Phones/Output jack: Stereo standard jack

Audio input jack: Stereo mini jack (Input impedance: 9 k Ω , input sensitivity: 200 mV)

Power jack

DC 24 V

Power supply

AC adaptor only

AC adaptor: AD-E24250LW

Auto power off: approximately 30 minutes after last operation; can be disabled

Speakers

10 cm x 2 (output: 15 W + 15 W)

Power consumption

24 V - 15 W

Dimensions

94,8 x 38,4 x 11,6 cm

Weight (without batteries)

approximately 7,0 kg (without batteries)