logo
Image not found or type unknown

Firma: Player Plus doo
Adresa: Svetogorska 9
Telefon: +381 11 3347 442
Fax: +381 11 3347 615
PIB: 106966344
E-mail: porudzbine@player.rs

CASIO WK-240
Image not found or type unknown

CASIO WK-240

Šifra: 11637
Kategorija prozivoda: Aranžerske Klavijature
Proizvođač: CASIO

Cena: 37.200,00 rsd

Keyboard
76 standard size keys
Touch Response: 2 types, Off
Maximum Polyphony
48 notes (24 for certain tones)
Tones
Built-in Tones: 600
Up to 8 (Melody Sampling: 5, Drum Sampling: 3)*, Up to 10 seconds
Functions: Layer, Split, Piano/Organ button
Effects
Hall effect button
Reverb
1 to 10, Off
Chorus
1 to 5, Off
Metronome
Beats per Measure: 0, 2 to 6
Tempo Range: 30 to 255
Song Bank
Built-in Songs: 152
User Songs: Up to 10*
Step Up Lesson
Lessons: 4 (Listen, Watch, Remember, Auto)
Lesson Part: L, R, LR
Functions: Repeat, Voice Fingering Guide, Note Guide, Performance Evaluation
Music Challenge
20 notes
Auto Accompaniment
Built-in Rhythms: 180
User Rhythms: Up to 10 (Accompaniment Edit)*
Chord Book Function
Chord guide
Registration
32 (4 setups × 8 banks)
Recorder
Real-time recording, playback
Keyboard Play: 5 songs, 6 tracks
Playing Along with a Built-in Songs: 1 song (L, R, LR)
Memory Capacity: Approximately 12,000 notes (total for 6 songs)
Other Functions
Transpose: ±1 octaves (–12 to +12 semitones)
Octave Shift: Upper/Lower ±2 octaves

Tuning: A4 = 415.5 to 465.9 Hz (Initial Default: 440.0 Hz)
Preset Scales: 17
Music Preset: 305
One Touch Preset: 180
Auto Harmonize: 12 types
Arpeggiator: 90 types
MIDI
16 multi-timbre received, GM Level 1 standard
Musical Information Function
Tone, Rhythm, Song Bank numbers and names, staff notation, fingering, pedal operation, tempo, measure and beat number, chord name, etc.
Inputs/Outputs
USB-Port: TYPE B
Sustain/Assignable jack: Standard jack (sustain, sostenuto, soft, rhythm)
Phones/Output jack: Stereo standard jack;
Output Impedance: 140 Ω; Output Voltage: 4.5V (RMS) MAX
Audio In jack: Stereo mini jack
Input Impedance: 9kΩ
Input Sensitivity: 200mV
Mic In/Sampling jack: Standard jack
Input Impedance: 3kΩ, Input Sensitivity: 10mV
Power Jack
DC9.5V
Power Supply
2-way
Batteries: 6 D-size zinc-carbon batteries or alkaline batteries
Battery Life: Approximately 3 hours continuous operation on alkaline batteries
AC Adaptor: AD-E95100L
Auto Power Off: Approximately 5 hours continuous operation on zinc-carbon batteries
Speakers
12cm × 2 (Output: 2.5W + 2.5W)
Power Consumption
9.5V = 7.7W
Dimensions
116.1 × 38.5 × 13.4 cm (45 3/4 × 15 3/16 × 5 1/4 inch)
Weight
Approximately 6.9kg (15.2 lbs) (without batteries)

Cene su informativnog karaktera. Prodavac ne odgovara za tačnost cena iskazanih na sajtu, zadržava pravo izmena cena. Ponudu za ostale artikle, informacije o stanju lagera i aktuelnim cenama možete dobiti na upit. Plaćanje se isključivo vrši virmanski - bezgotovinski.