

ARCAM ST25 Streamer Mrežni plejer

Šifra: 19465
Kategorija proizvoda: Network Plejeri
Proizvođač: ARCAM

Cena: 179.880,00 rsd

ARCAM ST25 Streamer Mrežni plejer

Exquisite sound quality has been achieved through thoughtful engineering of a new 6-layer digital audio and streaming platform which includes a ground plane through the entire board to keep noise and interference away from the sensitive audio components. These components include the latest Hyperstream iV DAC topology from ESS, in a balanced configuration with advanced jitter elimination. Sound quality is enhanced further with

a new linear toroidal transformer power supply design that drives the entirety of the internal operation with lower noise, and a switching supply that only operates for peak efficiency when in standby.

Up front, the ST25 features a new, bonded 6.5" high-resolution display to show album artwork and metadata which is clearly legible from the comfort of your preferred armchair. For playback, an inclusive feature set supports most smart phones and tablets, as well as popular streaming services. Connecting the ST25 to your home network with Wi-Fi is quick and straightforward with our ARCAM Radia App. Once connected, enjoy instant playback using Apple Airplay, Google Cast, Spotify Connect, Tidal Connect, and Roon (coming soon).

The ARCAM ST25 is the ultimate high resolution audio upgrade for any Hi-Fi system, especially the ARCAM Radia A25. It includes a control link for ARCAM Radia amplifiers, allowing the 2 components to act as one from your device. Sonically, this combination offers pure audio paradise, thanks to the benefits of isolated components with individual power supplies.

- All new, ultra High-Resolution Streaming Platform to deliver on sound quality and user experience
- New Linear power supply design to deliver peak sound performance
- High-resolution display for clearly visible album artwork and metadata
- Perfect match for the ARCAM A25 integrated amplifier
- Supports Apple Airplay, Google Cast, Spotify Connect and Tidal Connect
- Setup with ARCAM Radia App for presets, Internet Radio and Podcasts
- Supports up to 32 bit / 384 kHz Hires audio
- Roon Ready (coming soon)
- Plastic free packaging

Services

Works with (apps):

ARCAM Radia
Spotify (Connect)
Tidal (Connect)
Roon Ready (coming soon)

Works with (services):

Apple Airplay
Google Cast

ARCAM Radia supported services (Global):

Internet Radio
Podcasts
UPnP
USB Media (using USB-A mass storage input)

Audio Section

Supported media: FLAC, WAV (LPCM), AAC, ALAC, AIFF, DSD (up to 256), MP3, MP4, OGG, WMA

Supported Bit depth: 16, 24, 32

Supported sample rates (kHz): Up to 384 kHz

Gapless Playback: Yes

Digital Audio Outputs: 1x Coaxial (RCA), 1x Optical (Toslink)

Analogue Audio Outputs: 1x Stereo (RCA) pair

Wireless Specification

Wi-Fi Network: IEEE 8002.11 a/b/g/n/ac/ax (2.4GHz/5GHz)

2.4G Wi-Fi Transmitter Frequency Range and Power:

2400-2483.5 MHz (USA 11 Channels, Europe and Others 13 Channels) <20dBm

5G Wi-Fi Transmitter Frequency Range and Power:

5150-5250 MHz <23dBm, 5250-5350 MHz & 5470-5725 MHz <20dBm, 5725-5850 MHz <14dBm

General

Mains voltage: 100V or 110-120V or 220-240V, 50-60Hz

Power consumption: 15W

Power consumption (Eco standby): <0.5W

Dimensions W x D x H (including feet): 432 x 329 x 99mm

Weight (net): 5 kg

Weight (packed): 7 kg

Supplied accessories:

Mains lead(s)

Remote control with 2 x AAA batteries

Control Cable

Quick Start Guide

Important Safety Instructions