Firma: Player Plus doo
Adresa: Svetogorska 9
Telefon: +381 11 3347 442
Fax: +381 11 3347 615
PIB: 106966344
E-mail: porudzbine@player.rs

Pioneer XPRS102 - Aktivni zvučnik



Šifra: 17081
Kategorija prozivoda: Aktivne Zvučne Kutije
Proizvođač: Pioneer DJ

Cena: 95.880,00 rsd

The Pioneer XPRS102 features a 2000W Class-D amplifier that drives the 10" woofer and a 1" compression driver, which combine for a frequency response of 50 Hz to 20 kHz with a max SPL of 129 dB. The rear panel features a 3-input mixer with channel 1 offering a combo XLR-1/4" connector and gain control for microphone and line levels, while channel two offers a combo XLR-1/4" Hi-Z and line inputs with level gain control. Channel 3 boasts a 3.5mm line input. An XLR line output sums all channels together for adding additional speakers for better coverage. Other features include four EQ DSP modes including Live, Music, Speech, and Monitor.

Powerful Class-D Amplification
The XPRS2 Series employs Class-D amplification with high output wattage for a powerful and premiere audio experience for performers and listeners alike. The XPRS102 full-range speaker features Class-D 2000W amplification.

High-Quality and Robust Build
Pioneer DJ's all-new XPRS2 Series features a sleek all-black, protective plywood cabinet for performance in harsh indoor and outdoor environments. The series models all come with a durable handle to support system portability and handling during setup and take down. The XPRS2 Series also features rubber feet to create separation and shock absorption between surfaces.

Four DSP Modes
Both of the XPRS2 full-range speakers contain four different DSP preset modes: Live, Music, Speech, and Floor Monitor to address the needs of different listening environments.

XPRS102 Full-Range Speaker Design
The XPRS102 pairs a 10" woofer and 2.5" voice coil with a 1" exit compression driver and 1.75" voice coil to deliver pristine audio performance. Complete with a maximum sound pressure level (SPL) of 129 dB and frequency response of 50 Hz to 20 kHz, the XPRS102 full-range speakers help ensure music and spoken word reproduction is accurate and performs as intended.

Pioneer DJ XPRS102 Specs
Configuration Active 2-Way
Enclosure Type Bass-Reflex Loudspeaker
Total Power Capacity 2000 W Peak
1000 W Program
500 W RMS
Amplifier Class Class-D
Drivers
HF Driver 1 x 1" / 25.4 mm Titanium Compression Driver
HF Voice Coil 1.75" / 4.45 cm

LF Driver 1 x 10" / 25.4 cm Woofer
LF Voice Coil 2.5" / 6.3 cm
Performance
Frequency Response 50 Hz to 20 kHz -10 dB
Maximum SPL 129 dB (Peak)
Protections Overload, Signal Limiter, Thermal
Connectivity
Audio I/O 1 x Combo XLR-1/4" 3-Pin Female Balanced/Unbalanced Mic/Line Input
1 x Combo XLR-1/4" 3-Pin Female Balanced/Unbalanced Line/Hi-Z Input
1 x 1/8" / 3.5 mm TRS Female Unbalanced Line Input
1 x XLR 3-Pin Balanced Mix Output
Network I/O None
USB None
Wireless Connectivity None
Signal Processing
EQ None
Parametric EQ None
Semi-Parametric EQ None
Filters None
Dynamic Processing Compression, Limiter
Phase Adjustment None
Digital Signal Processing Voicing Modes
Power
AC Input Power 110 to 240 VAC, 50 / 60 Hz (T 10 A L 250 V)
AC Power I/O 1 x IEC Input
Power Consumption 800 W
Physical
Mounting 1 x 1.4" / 35 mm Pole Socket (Bottom)
10 x M10 Fly Point
Handles 1 x Each Side
Construction Material Plywood
Dimensions 20.5 x 12.2 x 11.8" / 520.7 x 309.9 x 299.7 mm
Weight 34.2 lb / 15.5 kg

Cene su informativnog karaktera. Prodavac ne odgovara za tačnost cena iskazanih na sajtu, zadržava pravo izmena cena. Ponudu za ostale artikle, informacije o stanju lagera i aktuelnim cenama možete dobiti na upit. Plaćanje se isključivo vrši virmanski - bezgotovinski.