

## Tascam MZ-223

Šifra: 17981  
Kategorija proizvoda: Studijske Miksete  
Proizvođač: TASCAM

Cena: **80.280,00** rsd

The MZ-223 allows multiple audio sources to be mixed, segregated, and routed to three independent main outputs. The rear panel offers five input channels with 10 sets of RCA stereo pairs for connecting a variety of equipment. Channels 1 and 2 also offer a switchable phono preamp for connecting turntables. Each of the three outputs offers a pair of balanced XLR and a pair of unbalanced RCA connectors. Additionally, the monitor output is offered on a pair unbalanced RCA connectors.

The front panel features five volume sliders for each of the line input channels. Each channel also offers A/B source select and output select buttons. There are three dedicated main outputs with dedicated volume control and 3-band EQ. The two microphone inputs offer combo XLR-1/4" inputs with dedicated output selectors, volume controls, and a 3-band EQ for each channel. Additionally, there is a "talkover" function, which ducks the music when the microphone is being used. The TASCAM MZ-232 ships with a power supply.

- Easy operation and routing via familiar volume sliders, toggle switches/buttons, and knobs
- Three independent Zone outputs with stereo XLR balanced and unbalanced RCA-type connectors per channel
- Five separate input channels, each with two sets of stereo RCA-type inputs
- Two additional mic-compatible XLR inputs on the front panel
- All audio can be mixed or segregated per channel, and routed to the three separate Zones/outputs
- "Talkover" function automatically lowers other source content while microphones are in use
- Independent three-band EQ per output channel and per microphone input
- Compact 2 RU rackmount design

### GENERAL

**Compatibility:** Not Specified by Manufacturer

### INPUTS / OUTPUTS

**Audio I/O:** 2 x Combo XLR-1/4" 3-Pin Mic Input  
10 x 2RCA TS Line Input  
6 x XLR 3-Pin Line Output  
3 x 2RCA TS Line Output  
1 x 2RCA TS Monitor Output  
1 x 1/4" TRS Headphone Output

**Mobile App Compatible:** No

\*As of March, 2023: Check with manufacturer for the most up-to-date compatibility

### POWER

**Power Source:** AC Adapter with Power Brick (Included)  
**AC Input Power:** 100 to 240 VAC, 50 / 60 Hz  
**DC Input Power:** 15 VDC  
**Power Consumption:** 35 W  
**Operating Current:** 2.4 A

### PHYSICAL

**Color:** Black

**Dimensions:** 19 x 5.2 x 3.5" / 48.3 x 13.2 x 8.9 cm

**Weight:** 5.5 lb / 2.5 kg

**PACKAGING INFO**

**Package Weight:** 6.8 lb

**Box Dimensions (LxWxH):** 20.3 x 6.5 x 5.9"