**logo**e not found or type unknown

Firma: Player Plus doo Adresa: Svetogorska 9 Telefon: +381 11 3347 442 Fax: +381 11 3347 615

PIB: 106966344

E-mail: porudzbine@player.rs

## ARCAM Radia A5 Integrisano Pojačalo

Šifra: 17967

Kategorija prozivoda: Integrisana Pojačala

Proizvođač: ARCAM

Cena: 71.880.00 rsd

ARGAM: Radia ASpIntegrisano Pojačalo

The "A" in

ARCAM stands for Amplification - this is our core competance. The A5 is the latest in more than 45 years of amplifier design and manufacture, going back to our first product in 1976 - the A&R Cambridge A60 amplifier. New components and materials have been painstakingly analysed and reviewed to ensure brilliant sound quality.

So you can play music straight out of the box, the ARCAM A5 includes a Bluetooth solution with Qualcomm AptX Adaptive technology. This provides up to 24-bit HD audio for the best sound quality from your phone or tablet, no matter what you are playing. It can also connect to Bluetooth headphones so your listening experience can continue sensitively after dark.

Hi-res audio is included with high resolution digital audio inputs included.

Like any ARCAM integrated amplifier, we pay particular attention to the built in phono stage to ensure your records sound as lush and engaging as possible.

ARCAM Class AB amplification - provides brilliant musicality 50W per channel (8 $\Omega$ ) - powers loudspeakers with ease Bluetooth with aptX<sup>M</sup> Adaptive Technology - for the best sou

Bluetooth with aptX™ Adaptive Technology - for the best sound with the most convenience

Specially selected components and materials - to deliver on sound quality Wired or Wireless Headphones - connect your headphones for quiet listeni

Wired or Wireless Headphones - connect your headphones for quiet listening with, or without wires All new Radia design - Purposeful yet playful

MM phono stage - ready for Turntables

Hi-Res Digital Audio Inputs

Plastic Free Packaging - for easy disposal of natural materials

Specification	
Continuous power output (0.5% THD), per channel	50W (8Ω), 75W (4Ω)
Harmonic distortion, 80% power, 8 $\Omega$ at 1kHz	0.003%
Number of analog inputs	3 (RCA pairs)
Signal-to-noise ratio (A-wtd, ref. 50W, 1V input)	106dB
Frequency response	20Hz—20kHz ± 0.2dB

Phono (MM) Input impedance	$47k\Omega + 100pF$
Phono (MM) Input frequency response (ref. RIAA curve)	20Hz—20kHz ± 1dB
Coaxial (RCA) supported sample rates (kHz)	192, 176.4, 96, 88.2, 48, 44.1
Optical (Toslink) supported sample rates (kHz)	192, 176.4, 96, 88.2, 48, 44.1
Supported bit depths (bit)	24, 16
Frequency response (filter 1)	20Hz—20kHz ± 0.2dB
Headphone output maximum output level (RMS) into $32\Omega/300\Omega$	2.5V/5V
Headphone load range	16Ω - 2kΩ
Mains voltage	100V or 110–120V or 220–240V, 50–60Hz
Power consumption (maximum)	350W
Power consumption (standby)	<0.5W
Dimensions W x D (including speaker terminals) x H (including feet)	431 x 344 x 83mm
Weight (net)	8kg
Weight (packed)	11kg
Supplied accessories	Mains lead(s), Remote control with 2 x AAA batteries, Quick Start Guide, Important Safety Instructions