

Biamp Community R.35COAX

Šifra: 20209

Kategorija proizvoda: Nazidni Zvučnici

Proizvođač: Biamp

Cena: 95.880,00 rsd



The compact R.35 model gives systems designers increased flexibility by offering vastly improved music playback, additional coverage patterns and higher output in attractive paintable enclosures. The R.35COAX uses a 1.25-inch exit HF compression driver, featuring Community's exclusive Tru-Phase phase plug and Carbon Ring Cone Technology. Also includes front-loaded LF drivers in highly reinforced enclosures for natural, non-resonant low-frequency reproduction, while identical voicing ensures a uniform listening experience.

Features

10" LF driver, 1.25" exit compression driver

70V/100V autoformer

200W continuous power handling @ 8 ohms

90°x90° nominal beamwidth

70Hz - 16kHz operating range

Specifications

Transducers: LF 1 x 10" carbon ring cone; coaxial HF - 1 x 1.25" exit compression driver

Operating Range: 70 Hz - 16 kHz

Sensitivity (1W/1m): 97 dB

Power Handling: 200W continuous @ 8 ohms

Continuous Max Output: 122 dB (128 dB Peak)

70V/100V Autoformer: 200W, 100W, 50W, 25W (@70V only)

Nominal Beamwidth (H x V): 90° x 90° (conical)

Finish: Light Grey, Black or White ABS matte plastic, paintable with dual-layer powder-coated steel with NeverWet™ treated grille

Dimensions: 11.0" H x 13.0" W x 13.5" D (279 x 330 x 343 mm)