

Korg VOLCA-FM2

Šifra: 20624

Kategorija proizvoda: Sound Moduli

Proizvođač: Korg

Cena: 18.500,00 rsd

Korg VOLCA-FM2 type unknown

Keyboard: Multi touch 27 key keypad

Synthesizer:

- Type: FM synthesis
- Maximum Polyphony: 6 voices
- Structure: 6 operators, 32 algorithms
- Number of Programs: 64
- Edit parameters: Modulator (Attack, Decay), Carrier (Attack, Decay), LFO (Rate, P.Depth), Algrtm, Randomize Available to edit full parameters for each

operator in Edit Mode

- Controls: Transpose, Velocity, Octave, Arp (Type, Div), Chorus Level, Reverb Level
- Arpeggiator Types: 9 (each 3 patterns of "Rise", "Fall", and "Random")
- Voice Modes: Poly, Mono, Unison

Effect: Chorus, Reverb

Sequencer:

- Number of Parts: 1
- Number of Steps: 16
- Number of Recording Patterns: 16
- Controls: Motion Sequence, Active Step, Warp Active Step, Pattern Chain, Metronome

Connectors:

- Audio Output: Headphones (3.5mm stereo mini jack)
- Sync:

Sync In (3.5mm monaural mini jack, Maximum input level: 20V)

Sync: Out (3.5mm monaural mini jack, Output level: 5V)

When two units of volca fm, available to export the sound programs and sequence data from a volca fm to the other one

MIDI:

IN □OUT

Note: 3.5mm stereo mini jack connector (type-A MIDI adaptor needed)

Available to convert and load SYS-EX/SYX files from Yamaha DX7

Power:

- Power Supply: AA alkaline battery x 6 or AA nickel-metal hydride battery x 6
Or AC adapter (DC 9V) (optional)

- Battery Life: Approximately 10 hours (using alkaline batteries)

Dimensions (W x D x H): 193 x 115 x 40 mm / 7.60" x 4.53" x 1.57"

Weight: 360 g / 12.70 oz. (Excluding batteries)

Others:

- Included Items: AA alkaline battery x 6 (for verifying operation), Sync Cable, Edit Parameter List
- Accessories: AC adapter (DC 9V) KA-350