

ARCAM RADIA A15+ - Integrisano pojačalo

Šifra: 20821

Kategorija proizvoda: Integrisana Pojačala

Proizvođač: ARCAM



Cena: 167.880,00 rsd

Continuous power output (0.5% THD), per channel

2 channels driven, 20Hz - 20kHz, 8Ω 80W

2 channels driven, 1kHz, 4Ω 120W

Harmonic distortion, 80% power, 8Ω at 1kHz 0.002%

Analogue Inputs

Number of inputs 3 (RCA pairs)

Signal/noise ratio (A-wtd, ref. 50W, 1V input) 106dB

Frequency response 20Hz—20kHz $\pm$ 0.2dB

Phono (MM) Input

Input impedance 47kΩ + 100pF

Frequency response (ref. RIAA curve) 20Hz—20kHz $\pm$ 1dB

Digital Inputs

Supported Sample Rates (kHz)

192, 176.4, 96, 88.2, 48, 44.1

Bit depths (bit) 24, 16

Frequency response (filter 1) 20Hz—20kHz $\pm$ 0.2dB

Signal/noise ratio (A-wtd, ref. 50W, 0dBFS) 109dB

Headphone Output

Maximum output level (RMS) into 32Ω/300Ω 2.5V/5Vrms

Load range 16Ω - 2kΩ

Wireless Specifications

Bluetooth Version - 5.4; A2DP Sink/Source, AVRCP, BLE, SBC, AAC, aptX, aptX HD and aptX Lossless, LE Audio, Auracast

Bluetooth Transmitter Frequency and Power - 2,400 MHz to 2,483.5 MHz: <20dBm

General

Mains voltage 100V or 110-120V or 220-240V, 50-60Hz

Power consumption (maximum) 500W

Power consumption (standby) <0.5W

Dimensions W x D (including speaker terminals) x H (including feet) 431 x 344 x 98mm

Weight (net) 10kg

Weight (packed) 13kg

Supplied accessories

Mains lead(s)

Remote control with 2 x AAA batteries

Quick Start Guide

Important Safety Instructions