

ARCAM RADIA A5+ - Integrirano pojačalo

Šifra: 20823
Kategorija proizvoda: Integrirana Pojačala
Proizvođač: ARCAM



Cena: 107.880,00 rsd

Continuous power output (0.5% THD), per channel

2 channels driven, 20Hz - 20kHz, 8Ω 50W
2 channels driven, 1kHz, 4Ω 75W
Harmonic distortion, 80% power, 8Ω at 1kHz 0.003%

Analogue Inputs

Number of inputs 3 (RCA pairs)
Signal/noise ratio (A-wtd, ref. 50W, 1V input) 106dB
Frequency response 20Hz—20kHz \pm 0.2dB

Phono (MM) Input

Input impedance 47kΩ + 100pF
Frequency response (ref. RIAA curve) 20Hz—20kHz \pm 1dB

Digital Inputs

Supported Sample Rates (kHz)
192, 176.4, 96, 88.2, 48, 44.1

Bit depths (bit) 24, 16

Frequency response (filter 1) 20Hz—20kHz \pm 0.2dB
Signal/noise ratio (A-wtd, ref. 50W, 0dBFS) 109dB

Headphone Output

Maximum output level (RMS) into 32Ω/300Ω 2.5V/5V
Load range 16Ω - 2kΩ

Wireless Specifications

Bluetooth Version - 5.4; A2DP Sink/Source, AVRCP, BLE, SBC, AAC, aptX, aptX HD and aptX Lossless, LE Audio, Auracast
Bluetooth Transmitter Frequency and Power - 2,400 MHz to 2,483.5 MHz: <20dBm

General

Mains voltage 100V or 110-120V or 220-240V, 50-60Hz
Power consumption (maximum) 350W
Power consumption (standby) <0.5W
Dimensions W x D (including speaker terminals) x H (including feet) 431 x 344 x 83mm
Weight (net) 8kg

Weight (packed) 11kg

Supplied accessories

Mains lead(s)

Remote control with 2 x AAA batteries

Quick Start Guide

Important Safety Instructions