

## MARTIN WISMAN MXR 1000



Šifra: 7084

Kategorija proizvoda: PA Rack

Proizvođač: Martin Wisman

**Cena: 31.080,00 rsd.**

### 2 Channel Mixer

#### Features

- \* 2 channel mixer of 10 inputs
- \* Remote paging console GMZ 200 as mic 1 with highest input priority
- \* Mic 2-4 with VOX selector over inputs 5-10 and phantom power
- \* All the 10 inputs with mic, line and high pass filtering selector
- \* Inputs 7-10 either by XLR mic inputs or by dual RCA line inputs
- \* Dual channel XLR line outputs
- \* All inputs include inputs 1-10, MIC (remote paging console GMZ 200), chime could be selected to have channel 1, channel 2 and channel 1+2 outputs.
- \* Built-in 2/4 tone pre-set chime, remote chime trigger and local trigger on front panel
- \* Volume controls are provided over chime, MIC1, inputs 2-10, channel 1 and channel 2 masters. Bass and treble tone control are provided for both channel 1 and channel 2.
- \* Indicators for input 1-10, power and 2 channel level meters
- \* AC 110 or 230V and DC 24V operation

### Specifications

Model	MXR 1000
Input Sensitivity/Impedance	
MIC/ Line	$\pm 2.45\text{mV}/5\text{K balanced}$ , $\pm 245\text{mV}/5\text{K balanced}$
Line RCA In	$500\text{mV}/5\text{K unbalanced}$
Output Level/Impedance	
Master 1, 2	$+4\text{dBu}/200\text{ balanced}$
REC	$0\text{dBu}/10\text{K unbalanced}$
Frequency Response	
Less Than	$-1\text{dB}(20\text{Hz}\sim 20\text{KHz})$
S/N Ratio	
MIC	More than 60dB
Line	More than 75dB
THD	
MIC	Less than 0.05%
Line	More than 0.03%
Cross-talk	
MIC	More than 60dB
Line	More than 75dB
Power Consumption Power	13W
Power Supply	$\sim 110\text{V}/60\text{Hz}$ or $\sim 230\text{V}/50\text{Hz}$ & DC 24V
Dimensions	484x295x44mm
Weight	3.9Kg

Pogledajte još:

**[Martin Wisman GMZ 200](#)**