

MARTIN WISMAN MXR 500

MARTIN WISMAN MXR 500

Mixer Pre-amplifier

Šifra: 07083  
 Kategorija proizvoda: PA Predpojačala  
 Proizvođač: Martin Wisman

The MXR 500 is a public address pre-amplifier with five balanced MIC inputs, three AUX level inputs and one EMC(priority) level inputs.

**Cena: 26.280,00 rsd**

Priority muting is achieved via MIC 2 and EMC for overriding music for paging and emergency alarms.  
 Individual gain controls are provided for MIC and AUX inputs, bass and treble controls are provided for overall tone control.

**Features**

- \* 5-channel MIC input and 3-channel Aux input.
- \* With 1-channel EMC input.
- \* Independent volume control, MASTER volume control.
- \* With compulsive insert and Priority function.
- \* MIC balance input interface with phantom power.
- \* Individual Gain controls for MIC
- \* EMC has priority over all inputs except MIC 2
- \* Bass and Treble Tone Controls
- \* AC 110V or 230V and DC 24V operation

Model	MXR 500
Input Sensitivity & Impedance	MIC 2, 3, 4, 5: ±2.5mV/2K?, Balanced XLR type MIC 2, 3, 4: 5mV/600?, Unbalanced TRS type AUX 1, 2, 3: 300mV/10K?, Unbalanced RCA type EMC: 775mV/47K?, Unbalanced TRS type MIC 1: ±385mV/20K?, Balanced MIC 1
Output Sensitivity & Impedance	MIX OUT: ±775mV/470?, Balanced XLR type REC OUT: 200mV/470?, Unbalanced RCA type
Frequency Response	20Hz-20KHz(±0.5dB)
S/N Ratio	MIC input: 66dB AUX input: 80dB
THD	Less than 0.1% at 1KHz, 1/3 rated power
Tone	Bass: ±10dB at 100Hz Treble: ±10dB at 10KHz
Mute	MIC 1 overrides other input signals with 0-30dB attenuation
Phantom Power	+48V
Protection	AC fuse
Power Supply	~110V/60Hz or ~230V/50Hz & DC 24V
Dimensions	484x295x44mm
Weight	5Kg

**Pogledajte još:**

**Martin Wisman GMZ 200**