

OMNITRONIC MPZ 350

Šifra: 1121

Kategorija proizvoda: 100V Pojačala

Proizvođač: Omnitronic

Cena: **56.899,00 rsd.**



6-zone PA mono mixing amplifier

Comfortable control of PA speakers via 6-zone technology

6 PA zone outputs, independently switchable on the front panel

Master PA output (70 V and 100 V)

Output for low-impedance speakers (4-16 ohms)

2 rear microphone inputs (6.3 mm jack, unbal.)

1 front microphone input (combination XLR/6.3 mm jack, unbal.) with adjustable priority
2 rear microphone inputs with separate level controls

3 line inputs (stereo RCA) with separate level controls

1 line output (stereo RCA)

Chime, switchable

Treble and bass control for the 9400 LED level display

Master control for the output signal

Protection circuits with LED indication: over current, short circuit, turn-on delay
· Rack installation, brackets detachable

| | |
|---------------------|----------------------------------|
| Power supply: | 230 V AC, 50 Hz ~ |
| Output power: | 350 W RMS |
| Output type: | 70 V, 100 V or 4-16 ohms |
| Output current: | 5 A (70 V), 3.5 A (100 V) |
| Mic inputs: | 5 mV, 600 ohms |
| Line inputs: | 300 mV, 10 kohms |
| Speaker connectors: | Screw connectors, terminal block |
| Frequency range: | 80 Hz - 16 kHz |
| Distortion: | 0.5 % (1 kHz) |
| S/N ratio: | 85 dB (line), 75 dB (mic) |
| Dimensions: | 483 x 385 x 92 mm |
| Weight: | 16 kg |